



Kofax Micro Card Reader User Guide

June 30, 2022

Version 4.0

Contents

Introduction.....	4
Purpose.....	4
Kofax Micro card reader	4
Hardware versions.....	5
Hardware part numbers	5
Default configurations	6
Included items	7
Compatibility	8
Imaging products	8
Kofax Business Connect	8
Installation.....	9
In an HP HIP2 pocket	9
In a standard MFP pocket.....	10
In the external housing	11
Opening the external housing	12
Installing a Secure Access Module (SAM)	12
Removing a Secure Access Module (SAM)	13
Usage	14
Presenting cards	14
Presenting Android devices	14
Presenting Apple devices.....	14
Beeper	15
LED indicator.....	15
Configuration	15
Setting the operating mode.....	16
Restricting operation to certain card types	17

Enabling keyboard emulation	18
Loading a custom configuration file	19
Updating reader firmware	20
Card Testing	21
Reading card numbers	21
Reading card types	22
Troubleshooting	23
Card not detected by reader	23
Reader responds to card, MFP does not respond	24
Reader not responding, LED off	25
Reader LED is the wrong color	26
Customize reader operation fails	26
Reader disappears following reset or reconnection not possible message	27
Technical Reference	28
Low frequency (125/134 kHz) card support	28
High frequency (13.56 MHz) card support	29
USB interface specifications	30
Keyboard emulations	30

Introduction

Purpose

This user guide provides information on the Kofax Micro card reader, intended for imaging professionals involved in the deployment of Kofax' Business Connect, ControlSuite, Copitrak, Equitrac, Output Manager, and SafeCom products.

Kofax Micro card reader

The Kofax Micro card reader is a USB connected RFID reader that allows users to authenticate themselves to Kofax products using their contactless ID card, badge, tag, or key fob. It replaces the Copitrak ID card reader, Equitrac ID card reader, and Kofax MX card reader.

Micro reader features include:

- module format allowing direct installation within an MFP pocket
- multiple cables to support a variety of internal pocket connections
- snap-together housing and long cable for traditional external use cases
- integration with Kofax Business Connect

Hardware versions

The Kofax Micro card reader comes in several versions:

- Multi-Card**
 Built with an NXP chipset, the Multi-Card reader supports a wide variety of 125 kHz RFID and 13.56 MHz contactless smartcard technologies based on ISO14443 and ISO15693 standards.
- Legic, iClass and Legic**
 Built with a LEGIC chipset, the Legic / iClass and Legic readers support a wide variety of 125 kHz RFID and 13.56 MHz contactless smartcard technologies based on ISO14443 and ISO15693 standards. They can retrieve encrypted data from iCLASS (not including iCLASS SE or Seos), LEGIC Prime, and LEGIC Advant secure credentials.
- iClass Seos + Multi-Card**
 Built with an NXP chipset, the iClass Seos + Multi-Card reader supports a wide variety of 125 kHz RFID and 13.56 MHz contactless smartcard technologies based on ISO14443 and ISO15693 standards. It contains an iCLASS SE Processor to decrypt the Physical Access Card System (PACS) data from iCLASS, iCLASS SE, and iCLASS Seos secure credentials.

Hardware part numbers

Each version is identified by a unique hardware part number:

Version	Reader Part Number	Boxed Part Number
Multi-Card	Y591-MMUL-202	Y10B-MMUL-202
	Y591-MMUL-212	Y10B-MMUL-212
Legic	Y591-MLG2-202	Y10B-MLG2-202
iClass and Legic	Y591-MLGI-212	Y10B-MLGI-212
iClass Seos + Multi-Card	Y591-MMSI-202	Y10B-MMSI-202
	Y591-MMSI-212	Y10B-MMSI-212

Micro readers with part numbers ending in -212 ship with Kofax Business Connect compatibility enabled, replacing the original -202 parts which did not. These -202 readers can be upgraded to support Business Connect by programming them with any Stock Solution using Kofax Reader Maintainer version 2.12.00 (or above).

The Legic reader was replaced by the iClass and Legic reader. It can be upgraded with iClass support by programming the “iCLASS, LEGIC (Types 96, 24, 50, 192)” Stock Solution using Kofax Reader Maintainer 2.12.00 (or above).

Refer to the section “Restricting operation to certain card types” for details.

Default configurations

The Kofax Micro card reader ships with various configurations:

Version	Keyboard Emulation	Beeper	Returns
Multi-Card	Disabled	Enabled	Unique ID (UID) or Card Serial Number (CSN) from all hardware supported card types
Legic	Disabled	Enabled	Unique ID (UID) from LEGIC Prime and Advant cards Other card types and formats ignored
iClass and Legic	Disabled	Enabled	Card Number from the Physical Access Control System (PACS) data in iCLASS cards formatted as: <ul style="list-style-type: none"> • 26-bit Wiegand / H10301 • 37-bit H10302 • Corporate 1000 35-bit • Corporate 1000 48-bit Unique ID (UID) from LEGIC Prime and Advant cards Other card types and formats ignored
iClass Seos + Multi-Card	Disabled	Enabled	Card Number from the Physical Access Control System (PACS) data in iCLASS, iCLASS SE, or iCLASS Seos cards formatted as: <ul style="list-style-type: none"> • 26-bit Wiegand / H10301 • 37-bit H10302 • Corporate 1000 35-bit • Corporate 1000 48-bit Other card types and formats ignored

Readers can be configured to enable keyboard emulation, disable the beeper, accept only certain card types, or modify the output format. Consult the “Configuration” section for details.

Important: Keyboard emulation must be enabled before connection to Copitrak terminals and MFP clients.

Included items

Each Kofax Micro card reader ships with the following:

- reader module
- two-piece snap together external housing
- 6 foot / 1.8 m cable with USB A plug for use with external housing
- 4 inch / 10 cm cable with USB mini-B plug for use in HP HIP2 pockets
- 5 inch / 12 cm cable with USB A plug for use in generic MFP pockets
- 20 inch / 50 cm cable with USB mini-B plug for use in generic MFP pockets
- two double-sided adhesive strips
- two self-adhesive Velcro fasteners
- two cable ties

Certain HP HIP1 pockets require a 6 inch / 15 cm cable with USB mini-B socket. This item is sold separately, consult your Kofax sales representative for details.

Compatibility

Imaging products

The Kofax Micro card reader is compatible with the following products:

Product	Notes
Kofax Business Connect	Version 8.0 or higher When used with Kofax Equitrac or Kofax Output Manager products
Kofax ControlSuite	When used with Kofax Equitrac or Kofax Output Manager products
Kofax Copitrak	Must be configured with keyboard emulation enabled
Kofax Equitrac	Some embedded clients require keyboard emulation enabled
Kofax Output Manager	Version 5.0 or higher Some embedded clients require keyboard emulation enabled
Kofax SafeCom	Appropriate SafeCom Go version must be installed Some embedded clients require keyboard emulation enabled

Kofax Business Connect

The Kofax Micro card reader supports authentication and job release with the Business Connect mobile app.

Business Connect is supported by the following Equitrac embedded clients:

- Brother Unified Client (where device allows)
- Canon MEAP Embedded
- Fuji-Xerox ECSP (where device allows)
- HP OXP
- HP Unified Client
- Lexmark eSF
- Ricoh PCC 4
- Ricoh PCC 5 / Unified Client for Ricoh SOP
- Samsung Smart UX Unified Client
- Toshiba Unified Client (where device allows)
- Xerox ECSP (where device allows)
- Xerox EIP (where device allows)

Installation

In an HP HIP2 pocket

1. Use the 4 inch / 10 cm discrete wired cable:




2. Insert the small white end of the cable into the Kofax Micro card reader with the contacts facing down, and push the connector in until it clicks:



3. Pry the pocket cover open with a small flat bladed screwdriver:



4. Connect the USB mini-B Plug to the socket in the MFP pocket, and place the reader in the pocket with the antenna (larger) side facing up:



5. Snap the MFP cover shut, and install the Place Card Here sticker on the center of the cover:



In a standard MFP pocket

1. Consult the MFP manufacturer's documentation for the pocket location and opening instructions.
2. Select the shortest cable with the appropriate connector for the MFP.
3. Insert the small white end of the cable into the Kofax Micro card reader with the contacts facing down, and push the connector in until it clicks:



4. Fasten the antenna (larger) side of the reader to the MFP pocket cover with the double side tape provided:



5. Connect the USB cable to the socket in the MFP and follow the manufacturer's instructions for reassembly.
6. Install the Place Card Here sticker on the pocket cover directly over the center of the concealed reader:



In the external housing

1. Select the 6 foot / 1.8 m cable:



2. Insert the small white end of the cable into the Kofax Micro card reader with the contacts facing down, and push the connector in until it clicks:



3. Place the reader in the upper housing, routing the cable through the wider strain relief feature:



4. Slide the bottom of the housing into the upper piece so that the loops engage the tabs:



5. Press the cable end of the housing down until the pieces snap together:



Opening the external housing

1. Firmly pull the housing pieces apart while pushing a flat-bladed screwdriver into the release slots:



Installing a Secure Access Module (SAM)


1. Position the reader module with the antenna (larger) side facing up:



2. With the SAM contacts down and the notch facing out, insert the SAM into the slot:




3. Use the edge of a coin or a flat-bladed screwdriver to push the SAM completely inside the reader slot:



Removing a Secure Access Module (SAM)

1. Grasp the SAM with a pair of tweezers and pull firmly to extract:



Usage

Presenting cards

Cards should be placed and held within approximately 1/4 inch (6 mm) of the Kofax Micro card reader until success is indicated by the LED or beeper.

Moving or 'swiping' the card across the reader like a traditional magnetic stripe card can disrupt the RFID link and should be avoided.

Presenting Android devices

The Kofax Business Connect application, when combined with Kofax Equitrac or Kofax Output Manager, uses Near Field Communication (NFC) on Android mobile devices for print release and authentication. The device should be presented to the reader with its NFC coil squarely centered over the reader module or housing. The location of this coil varies but is often on the back of the mobile device centered across its width, in either the top half of the device or directly in the middle.

Presenting Apple devices

The Kofax Business Connect application, when combined with Kofax Equitrac or Kofax Output Manager, uses the Low Energy radio on Apple devices for print release and authentication. The mobile device should be presented with its low energy radio antenna centered over the face of the reader module or housing, as close to it as possible. This antenna is at the top left corner of an iPhone, and to the right of the Home button on the bottom edge of an iPad.

Due to the range of the radio signal, the Business Connect app can 'see' all readers in a radius of approximately 30 feet (10 m). The app monitors the Received Signal Strength Indication (RSSI) from each reader to determine when a specific reader is close enough to trigger authentication. This takes a second or so to complete after the device has been presented.

If consistent authentication problems occur with specific mobiles, the RSSI threshold can be tuned in the Admin Tools page of the Business Connect server. This setting applies to all instances of the Business Connect mobile app logged in to that server. The more negative the threshold, the more easily the app authenticates with readers which are farther away.

Important: The RSSI threshold should only be adjusted by 1 or 2 dB at a time. Lowering it too far reduces security, as the mobile app may not discriminate between readers on printers placed side by side or on opposite sides of a wall. This can result in the inadvertent release of print jobs to the wrong location.

Beeper

Kofax Micro card readers contain a beeper which sounds whenever data is received from a presented card or mobile device.

The Reader Maintainer software is used to enable or disable the beeper, but its volume is not adjustable. Refer to the section “Setting the operating mode” for details.

Note: Some MFPs sound the reader’s beeper regardless of the reader configuration.

LED indicator

The LED in the Kofax Micro card reader is green when it has power, blinking off and back to green when data is read from the presented card or mobile device. Readers configured in MX Compatible mode use a red LED instead of green.

Note: Some MFPs control the color and flash rate of the LED to reflect their login state and system status, regardless of the mode setting.

Configuration

Kofax Micro card readers are configurable to:

- select an operating mode compatible with the target use case
- restrict operation to certain card technologies
- enable keyboard emulation as required by some MFP clients and terminals
- adapt the reader to specific customer card system requirements
- update the firmware to support new card types or features


Readers are configured with the Reader Maintainer software, available at delivery.kofax.com.

Setting the operating mode

Kofax Micro card readers ship from the factory with a green LED, the beeper enabled, and data output in decimal form (octal for HID Prox cards). For compatibility with other readers in a mixed fleet however, Micro readers are configurable in various modes.

The Reader Maintainer (RM) software configures the operating mode:

1. Launch the RM software.
2. Connect the reader to the PC or laptop running the RM.
3. If the reader's serial number and other details do not appear in the main window, ensure that it is the only reader connected to the computer.
4. Click Customize Reader.
5. Select the desired Mode:



Mode	LED	Beeper	Data Format
Default	Green	Enabled	Decimal, octal for HID Prox cards
Silent	Green	Disabled	Decimal, octal for HID Prox cards
MX Compatible	Red	Enabled	Compatible with Kofax MX card readers for SafeCom

Note: Silent mode is compatible with first generation Equitrac USB card readers.

Important: Be sure to select keyboard emulation (as shown above) when using readers with Copitrac clients and terminals.

6. Click Update Reader, then Yes, and wait for the progress bar to complete.
7. If configuring multiple readers, disconnect the initial reader, connect the next one, and repeat from step 6.
8. When finished, close the dialog.


Note: The Customize Reader dialog always opens to the last mode selected.

Restricting operation to certain card types

Kofax Micro card readers allow a user to authenticate by presenting their RFID badge or key fob. Some users carry these in a wallet or purse along with other RFID-enabled credentials for banking, credit, or customer loyalty. Restricting readers to work only with the desired card type avoids invalid logins or “swipe to logout” workflows triggered by other credentials.


Use the Reader Maintainer (RM) software to restrict a reader to the desired card type:

1. Launch the RM software.
2. Connect the reader to the PC or laptop running the RM.
3. If the reader’s serial number and other details do not appear in the main window, ensure that it is the only reader connected to the computer.
4. Click Customize Reader.
5. Select a Stock Solution compatible with the desired card type:



Note: To determine your card type, refer to the “Reading card types” section.

6. Select a keyboard emulation option, if required:



Important: All Copitrak MFP clients and terminals require keyboard emulation.

7. Click Update Reader, then Yes, and wait for the progress bar to complete.
8. If configuring multiple readers, disconnect the initial reader, connect the next one, and repeat from step 7.
9. When finished, close the dialog.


Note: The updated reader can be tested with the Read Card Number function.

Enabling keyboard emulation

Certain MFP clients and all Copitrak terminals require Kofax Micro card readers to emulate a USB keyboard, with some clients also needing a ^ character ahead of the card data to differentiate it from regular keyboard input. This is complicated by the various international keyboard layouts placing the ^ symbol on different keys.

Use the Reader Maintainer (RM) software to enable keyboard emulation:

1. Launch the RM software.
2. Connect the reader to the PC or laptop running the RM.
3. If the reader's serial number and other details do not appear in the main window, ensure that it is the only reader connected to the computer.
4. Click Customize Reader.
5. Select the desired Mode and Stock Solution.
6. Select a keyboard emulation from the drop list:



Note: The “Keyboard emulation” section describes the available options.

7. Click Update Reader, then Yes, and wait for the progress bar to complete.
8. If configuring multiple readers, disconnect the initial reader, connect the next one, and repeat from step 7.
9. When finished, close the dialog and exit the software.

Note: Some MFPs must be set up with the reader's USB Vendor and Product ID (VID and PID) to enable support. The Kofax Micro card reader uses VID 5037 (hexadecimal 13AD) and PID 40106 (hexadecimal 9CAA) when configured with keyboard emulation.


Loading a custom configuration file

It may be necessary to customize a Kofax Micro card reader to:

- accept a specific combination of card types
- access an authenticated or encrypted card system
- read data from specific card memory locations
- trim card data prior to output
- output data in formats matching a pre-existing user database

Customizations are created by Kofax Support and distributed as .bec files. These files are loaded with the Reader Maintainer (RM) software:

1. Launch the RM software.
2. Connect the reader to the PC or laptop running the RM.
3. If the reader's serial number and other details do not appear in the main window, ensure that it is the only reader connected to the computer.
4. Click Customize Reader.
5. Click the Custom Solution button.
6. Click Browse... then navigate to and Open the desired .bec file.
7. Select a keyboard emulation option, if required:



Note: The “Keyboard emulation” section describes the available options.

8. If alternate firmware is provided, the .bf2 file is also selected at this time.
9. Click Update Reader, then Yes, and wait for the progress bar to complete.
10. If configuring multiple readers, disconnect the initial reader, connect the next one, and repeat from step 9.
11. When finished, close the dialog.

Note: The updated reader can be tested with the Read Card Number function.

Updating reader firmware

Kofax Micro card readers may require updated firmware to support new card types or customization features. Reader firmware is distributed as .bf2 files.

Use the Reader Maintainer (RM) software to update the firmware:

1. Launch the RM software.
2. Connect a reader to the PC or laptop running the RM.
3. If the reader's serial number and other details do not appear in the main window, ensure that it is the only reader connected to the computer.
4. Click Customize Reader.
5. Click the Custom Solution button.
6. Click Browse... then navigate to and Open the desired .bf2 file.
7. If the new firmware is part of a customization, the associated .bec file and a keyboard emulation option are also selected at this time.

Note: The "Keyboard emulation" section describes the available options.

8. Click Update Reader, then Yes, and wait for the progress bar to complete.
9. If updating multiple readers, disconnect the initial reader, connect the next one, and repeat from step 8.
10. When finished, close the dialog.


Note: The updated reader can be tested with the Read Card Number function.

Card Testing

Reading card numbers

The Reader Maintainer (RM) software shows the output from a Kofax Micro card reader:

1. Launch the RM software.
2. Connect the reader to the PC or laptop running the RM.
3. If the reader's serial number and other details do not appear in the main window, ensure that it is the only reader connected to the computer.
4. Click Read Card Number.
5. Present cards to the reader one at a time, the most recent data highlights in red:



The value in the Number column is the reader output. It's dependent on the reader configuration controlling the card type(s) to read, the data fetched for each type, and the output data format.

A Unique ID (UID) or Card Serial Number (CSN) is also displayed but can be different than the output in the Number column, particularly when working with encrypted cards.

Note: Refer to the topic “Card not detected by reader” in the Troubleshooting section if no data appears when a card is presented.


6. When finished, close the dialog.

Note: The Read Card Number function shows the *output* from a card, the Read Card Type function shows the *type* of card you have.

Reading card types

The Reader Maintainer (RM) software is used to read the card type:

1. Launch the RM software.
2. Connect a reader to the PC or laptop running the RM.
3. If the reader's serial number and other details do not appear in the main window, ensure that it is the only reader connected to the computer.
4. If the main window lists a configuration other than All Types, use the Customize Reader function to load the Stock Solution "All hardware supported card types".
5. Click Read Card Type.
6. Present cards to the reader one at a time, the most recent card appears in red:



Note: See "Restricting operation to certain card types" for details on using the Card Type information displayed.

7. When finished, close the dialog.

Note: The Read Card Type function shows the *type* of card you have, the Read Card Number function shows the configuration-dependent *output* from that card.

Troubleshooting

Card not detected by reader

Condition

The reader LED is lit, but there is no response (beeper, LED, or MFP client action) when a card is presented.

Cause 1

The reader is loaded with an incompatible configuration.

Remedy 1

Use the Reader Maintainer (RM) software's Customize Reader function to load the Stock Solution "All hardware supported card types", then test using the RM's Read Card Number function.

Cause 2

The card uses random UIDs instead of a fixed UID value. Random UIDs prevent the association of cards to specific users, so are suppressed by the reader to avoid nuisance workflows.

Remedy 2

Use the Reader Maintainer software's Read Card Type function to identify the card. If a Card Type and UID appear, then withdraw the card and present it again. If a different UID appears then the card is randomizing its UID and some other data must be retrieved for authentication.

Contact Kofax Support to obtain a solution for your card type.

Cause 3

The card is incompatible with the reader hardware.

Remedy 3

It may be possible to develop a custom solution for the target card system. Contact Kofax Support for assistance.

Reader responds to card, MFP does not respond

Condition

The reader beeps or its LED blinks in response to card presentations but there is no response from the MFP client.

Cause 1

The MFP client requires the reader to operate in keyboard emulation mode.

Remedy 1

Refer to the section “Enabling keyboard emulation” for further instructions.

Cause 2

Some MFP clients work only with specific USB ports.

Remedy 2

Consult the client documentation to ensure the reader is connected to the proper USB port.

Reader not responding, LED off**Condition 1**

There is no response to card presentations and the reader LED is off.

Cause 1

The reader has no power.

Remedy 1

Connect the reader to another MFP, PC, or laptop. If the LED lights, then there was an issue with the USB port on the original MFP. It may be disabled, or the MFP was in deep sleep. Consult the MFP documentation to resolve the issue.

Condition 2

The reader has been connected to another device, but the LED remains off.

Cause 2

The cable connection to the reader module is loose.

Remedy 2

The cable must be inserted into the module with the contacts facing down, then pushed until a slight click is felt:



Reader LED is the wrong color

Condition 1

The reader LED is not the expected color.

Cause 1

LED color is typically controlled by the reader configuration. When configured in Default or Silent mode the LED is green, when configured in MX Compatible mode the LED is red.

Remedy 1

Configure the reader in the desired mode. Refer to “Setting the operating mode” for details.

Condition 2

The reader is configured in the proper mode, but the LED is still the wrong color.

Cause 2

Some MFP clients control LED color to indicate login state or system status. Connect the reader to a PC or laptop and observe the LED, if the expected color appears then the client was controlling the LED.

Remedy 2

Consult the client documentation for LED color details and configuration options.

Customize reader operation fails

Condition

An error message appears after clicking Update Reader in the Reader Maintainer.

Cause

The reader’s USB Product ID changes while loading firmware or transitioning in and out of keyboard emulation mode. Windows loads a new driver the first time this happens for a given reader, if that takes too long due to background operations such as whole disk encryption or heuristic anti-virus scanning, the Update Reader operation fails.

Remedy

Disconnect and reconnect the card reader, wait for its information to appear in the main window, then click Update Reader again.

Reader disappears following reset or reconnection not possible message

Condition

The reader is invisible to the Reader Maintainer (RM) software after performing the disconnect and reconnect cycle advised by the RM.


Cause

There is a mismatch between the reader's current configuration and the driver that was originally loaded for it by Windows.

Remedy

Force Windows to re-install the reader drivers:

1. Press the <Windows> and <Pause/Break> keys simultaneously to open the System properties.
2. Select Device Manager from the Related Settings list.
3. Locate the USB Input Device with a yellow warning triangle, right-click it, then select Uninstall device:



4. Disconnect and reconnect the card reader. Windows automatically installs the correct drivers, and the Reader Maintainer can detect it again.

Technical Reference

Low frequency (125/134 kHz) card support

Card System	Multi-Card	Legic	iClass and Legic	iClass Seos + Multi-Card
AWID	Yes	Yes, 1	Yes, 1	Yes, 1
Cardax	No, 3	No, 3	No, 3	No, 3
Cotag	Yes	Yes, 1	Yes, 1	Yes, 1
Deister	Yes	Yes, 1	Yes, 1	Yes, 1
EM 4100/4102	Yes	Yes, 1	Yes, 1	Yes, 1
EM 4205/4305	Yes	Yes, 1	Yes, 1	Yes, 1
EM 4450/4550, 4469/4569	Yes	Yes, 1	Yes, 1	Yes, 1
FDX-B	No, 3	No, 3	No, 3	No, 3
G-Prox	Yes	Yes, 1	Yes, 1	Yes, 1
HID Indala ASP	Yes	Yes, 1	Yes, 1	Yes, 1
HID Indala ASP+	Yes, 2	Yes, 1, 2	Yes, 1, 2	Yes, 1, 2
HID Prox	Yes	Yes, 1	Yes, 1	Yes, 1
Hitag 1/2 (256, 2048)	Yes	Yes, 1	Yes, 1	Yes, 1
Hitag S	Yes	Yes, 1	Yes, 1	Yes, 1
Honeywell Nexwatch Quadrakey	Yes	Yes, 1	Yes, 1	Yes, 1
IDTECH	Yes	Yes, 1	Yes, 1	Yes, 1
ioProx	Yes	Yes, 1	Yes, 1	Yes, 1
Keri	Yes	Yes, 1	Yes, 1	Yes, 1
Miro	Yes	Yes, 1	Yes, 1	Yes, 1
Pyramid / Farpointe Data	Yes	Yes, 1	Yes, 1	Yes, 1
Q5	No, 3	No, 3	No, 3	No, 3
Radio Key / SecuraKey	Yes	Yes, 1	Yes, 1	Yes, 1
Sokymat Unique	Yes	Yes, 1	Yes, 1	Yes, 1
T5567/T5557	No, 3	No, 3	No, 3	No, 3
Tiris	No, 3	No, 3	No, 3	No, 3
Titan	No, 3	No, 3	No, 3	No, 3
Zodiac	No, 3	No, 3	No, 3	No, 3

1. Disabled by default. Configure the reader using the “All hardware supported types” or desired single card type Stock Solution to enable support.
2. Raw data stream or hash value only. The reader output can be used for auto-registration or added to the user database as an alternate PIN by the system administrator. There is no direct relationship to any number printed on the card or stored in the access control system database.
3. Support possible but not compatible as shipped. Contact your Kofax Sales Representative.

High frequency (13.56 MHz) card support

Card System	Multi-Card	Legic	iClass and Legic	iClass Seos + Multi-Card
Calypso	Yes	Yes, 1	Yes, 1	Yes, 1
CEPAS	Yes	Yes, 1	Yes, 1	Yes, 1
EM 4033/4035	Yes	Yes, 1	Yes, 1	Yes, 1
HID iCLASS	Yes, 2, 5	Yes, 1	Yes	Yes
HID iCLASS SE	Yes, 2, 5	Yes, 1, 2, 4	Yes, 1, 2, 4	Yes
HID iCLASS Seos	Yes, 2, 3, 5	Yes, 1, 2, 3, 4	Yes, 1, 2, 3, 4	Yes
Infineon my-d vicinity	Yes	Yes, 1	Yes, 1	Yes, 1
LEGIC Advant	Yes, 2, 4	Yes	Yes	Yes, 1, 2, 4
LEGIC Prime	No	Yes	Yes	No
Mifare Classic	Yes	Yes, 1	Yes, 1	Yes, 1
Mifare DESfire, -EV1 (2K, 4K, 8K)	Yes	Yes, 1	Yes, 1	Yes, 1
Mifare Plus (-S, -X, L1, L2, L3)	Yes	Yes, 1	Yes, 1	Yes, 1
Mifare Ultralight, -C	Yes	Yes, 1	Yes, 1	Yes, 1
Moneo	Yes	Yes, 1	Yes, 1	Yes, 1
NFC Forum Tag 1-4	Yes	Yes, 1	Yes, 1	Yes, 1
NXP iCode	Yes	Yes, 1	Yes, 1	Yes, 1
NXP SmartMX, ProX	Yes	Yes, 1	Yes, 1	Yes, 1
Pay Pass	Yes	Yes, 1	Yes, 1	Yes, 1
Pico Pass	Yes	Yes, 1	Yes, 1	Yes, 1
SLE44R35	Yes	Yes, 1	Yes, 1	Yes, 1
SLE66Rxx (my-d move)	Yes	Yes, 1	Yes, 1	Yes, 1
Sony FeliCa	Yes, 5	Yes, 1, 4	Yes, 1, 4	Yes, 1, 5
SRI4K, SRIX4K	Yes	Yes, 1	Yes, 1	Yes, 1
SRI512, SRT512	Yes	Yes, 1	Yes, 1	Yes, 1
Tag-it ISO	Yes	Yes, 1	Yes, 1	Yes, 1

1. Disabled by default. Configure the reader using the “All hardware supported types” or desired single card type Stock Solution to enable support.
2. Unique ID (UID) only. The reader output can be used for auto-registration or added to the user database as an alternate PIN by the system administrator. There is no direct relationship to any number printed on the card or stored in the access control system database.
3. iCLASS Seos UIDs are returned only from Seos cards ordered with UID randomization turned off, as randomized UIDs cannot be used for user identification.
4. Access to encrypted data not possible.
5. Access to encrypted data requires installation of a third-party Secure Access Module (SAM).

USB interface specifications

Parameter	Multi-Card	Legic	iClass and Legic	iClass Seos + Multi-Card
Data rate	USB 2.0 Full Speed (USB 1.1 compatible)			
Protocol	USB HID, USB HID Keyboard (when keyboard emulation enabled)			
Vendor ID (hex)	13AD			
Product ID (hex)	9CA5 (default), 9CAA (when keyboard emulation enabled)			
Input voltage	4.7 to 5.5 VDC			
Reported maximum current	300 mA	300 mA	300 mA	300 mA
Maximum operating current	210 mA	235 mA	235 mA	260 mA
Typical operating current	150 mA	165 mA	165 mA	175 mA

Keyboard emulations

While many MFP clients natively support Kofax Micro card readers, some require it to emulate a keyboard by returning data as if it were typed one digit at a time. Certain older clients also require a ^ character ahead of the keyboard data, a process complicated by the various international keyboard layouts placing the ^ symbol on different keys.

The Reader Maintainer's Customize Reader function presents mode-dependent keyboard emulation options:

Mode			Keyboard Emulation
Default	Silent	MX Compatible	
Default	Silent	MX Default	Disabled
Keyboard	Silent Keyboard	MX Keyboard	Returns card data as keystrokes
Keyboard, US ^	Silent Keyboard, US ^		Returns card data as keystrokes with leading ^ character (Shift + 6 key)
Keyboard, French ^	Silent Keyboard, French ^		Returns card data as shifted number strokes with leading ^ character (French ^ key)
Keyboard, German ^	Silent Keyboard, German ^		Returns card data as keystrokes with leading ^ character (German ^ key)
Keyboard, Nordic ^	Silent Keyboard, Nordic ^		Returns card data as keystrokes with leading ^ character (Shift + " key)
Keyboard, Turkish ^	Silent Keyboard, Turkish ^		Returns card data as keystrokes with leading ^ character (Shift + 3 key)

Note: All keyboard emulations send <Enter> as the final keystroke.

Note: When selecting a ^ option the language chosen must match the MFP's language setting.